

WH-L100 Datasheet

File Version: V1.0.0



1.Product overview

WH-L100 is LoRa module which supports standard LoRaWAN protocol and working frequency band of WH-L100: -L: 433Mhz or 470Mhz; -H: 868Mhz or 915Mhz. WH-L100 has concentrated power density and powerful anti-interference capacity. LoRa direct sequence spread spectrum technology can also bring further communication distance.

Module can work in $1.8V\sim3.6V$ and sleep mode current is only 2uA which can be applied in ultra-low power consumption application scenarios.

2.Product features

- Adopt standard LoRaWAN protocol
- ➤ 4500 meters transmission distance
- ➤ -130dBm receiving sensitivity
- Sleep mode current 2uA
- Internally installed watchdog
- ➤ Small size: 36.0 x 21.0 x 2.8mm, SMT encapsulation


3. Product specifications


| Parameter | | Description | |
|--------------------|-----------------------|---|--|
| | Frequency band | L: 433/470Mhz; H: 868Mhz/915Mhz | |
| | | Voltage: 1.8V~2.4V, transmitting power can be set | |
| | Transmitting power | from 10dBm to 17dBm. | |
| | | Voltage: 2.4V~3.6V, transmitting power can be set | |
| | | from 10dBm to 20dBm. | |
| Wireless parameter | Receiving sensitivity | -141dBm@0.146Kbps | |
| | | 4.5km. Test condition: clear weather, open area, | |
| | Transmission distance | maximum power, antenna gain 5dBi, height is | |
| | | greater than 2m, 2.5K air rate. | |
| | Antenna type | Bonding pad | |
| | Protocol | LoRaWAN | |
| | Data interface | Serial port with baud rate 1200bps~115200bps | |
| | Power supply | Single power supply: 1.8V~3.6V | |
| | | Transmitting current: 130mA@3.3V | |
| | Working current | Receiving current: 16mA@3.3V | |
| | | Waking up current: 15 μ A@3.3V | |
| Hardware parameter | Working temperature | -30℃~+80℃ | |
| | Storage temperature | -45℃~+90℃ | |
| | Working humidity | 10%~90%RH | |
| | Storage humidity | 10%~90%RH | |
| | Dimension | 36.0mm*21.0mm*2.8mm | |



| _ | | | | |
|---|--------------|----|-----|--|
| | Encapsulatio | [] | SMT | |

4.Product dimensions







5.Contact Us

Company: Jinan USR IOT Technology Limited

Address: Floor 11, Building 1, No. 1166 Xinluo Street, Gaoxin District, Jinan, Shandong, 250101, China

Web: www.usriot.com

Support: h.usriot.com

Email: sales@usr.cn

Tel: 86-531-88826739/86-531-55507297

6.Disclaimer

This document provides the information of WH-L100 products, it hasn't been granted any intellectual property license by forbidding speak or other ways either explicitly or implicitly. Except the duty declared in sales terms and conditions, we don't take any other responsibilities. We don't warrant the products sales and use explicitly or implicitly, including particular purpose merchant-ability and marketability, the tort liability of any other patent right, copyright, intellectual property right. We may modify specification and description at any time without prior notice.

7.Update History

2018-03-30 V1.0.0 established.